









## Bondable Resistors for Transducers – Selection Chart

GAGE PATTERN AND DESIGNATION Matrix is shown at actual size. Insert Desired S-T-C No. in Spaces Marked XX. See Note 1	RESISTANCE IN OHMS	DIMENSIONS			
		PATTERN		MATRIX	
		Length	Width	Length	Width
 N2B-TR-A02-00150 N2B-TR-A02-00175 N2B-TR-A02-00200 N2B-TR-A02-00250 N2B-TR-A02-00300 N2B-TR-A02-00400 N2B-TR-A02-00600 N2B-TR-A02-00650 N2B-TR-A02-00700	15	<b>N2B-A02, N2T-LT02</b>			
	17.5				
	20	6.1	3.3	7.6	4.8
	25	<b>N2B-A06</b>			
	30				
	40	4.8	3.3	6.1	4.6
	60	<b>N2T-LT10</b>			
	65				
	70	2.1	1.8	2.5	1.9
	 N2B-TR-A06-00150 N2B-TR-A06-00175 N2B-TR-A06-00200 N2B-TR-A06-00250 N2B-TR-A06-00300 N2B-TR-A06-00400 N2B-TR-A06-00600 N2B-TR-A06-00650 N2B-TR-A06-00700	15	N2B Balco resistors are available in our A02 and A06 sizes. N2T Nickel resistors are available in our LT02 and LT10 sizes. The standard resistance values for each are as shown. Custom resistance values are available for a small set-up charge and 500-piece minimum order.  Resistance tolerance is $\pm 1\%$ at $+75^\circ\text{F}$ [ $+24^\circ\text{C}$ ]. Recommended Uses: <ul style="list-style-type: none"> <li>span-shift-versus-temperature compensation</li> <li>temperature sensing</li> </ul> <b>A02 and A06 Construction</b> These resistors are made of Balco alloy, and normally manufactured and stocked in unencapsulated form, but can be supplied with a thin layer of polyimide film covering the grid. Solder tabs are left exposed for simplified lead connections. To include this feature add OPTION E2 to the resistor designation.  Examples: N2B-TR-A06-00200/E2. Resistance tolerance on Option E2 versions is $\pm 1.5\%$ at $+75^\circ\text{F}$ [ $+24^\circ\text{C}$ ].  Note: The A02 resistor is no longer offered in Nickel.  <b>LT02 and LT10 Construction</b> These resistors are made of high-purity Nickel. They are manufactured and stocked with E3 encapsulation as standard. Solder tabs are left exposed for leadwire connections.  Example: N2T-TR-LT02-00300/E3. Resistance tolerance remains $\pm 1\%$ at $+75^\circ\text{F}$ [ $+24^\circ\text{C}$ ].		
17.5					
20					
25					
30					
40					
60					
65					
70					
 N2T-TR-LT02-00100 N2T-TR-LT02-00125 N2T-TR-LT02-00150 N2T-TR-LT02-00200 N2T-TR-LT02-00225 N2T-TR-LT02-00300 N2T-TR-LT02-00400 N2T-TR-LT02-00450 N2T-TR-LT02-00500 N2T-TR-LT02-00600 N2T-TR-LT02-00720 N2T-TR-LT02-00800 N2T-TR-LT02-00900		10			
	12.5				
	15				
	20				
	22.5				
	30				
	40				
	45				
	50				
	60				
72					
80					
90					
 N2T-TR-LT10-00100 N2T-TR-LT10-00125 N2T-TR-LT10-00150 N2T-TR-LT10-00200 N2T-TR-LT10-00225 N2T-TR-LT10-00300 N2T-TR-LT10-00400 N2T-TR-LT10-00450 N2T-TR-LT10-00500 N2T-TR-LT10-00600 N2T-TR-LT10-00720 N2T-TR-LT10-00800 N2T-TR-LT10-00900	10	Note: The A02 resistor is no longer offered in Nickel.  <b>LT02 and LT10 Construction</b> These resistors are made of high-purity Nickel. They are manufactured and stocked with E3 encapsulation as standard. Solder tabs are left exposed for leadwire connections.  Example: N2T-TR-LT02-00300/E3. Resistance tolerance remains $\pm 1\%$ at $+75^\circ\text{F}$ [ $+24^\circ\text{C}$ ].			
	12.5				
	15				
	20				
	22.5				
	30				
	40				
	45				
	50				
	60				
72					
80					
90					
 N2A-XX-B31-01250 EA-XX-B31-02500 N2A-XX-B32-01000 EA-XX-B32-02000 N2A-XX-B34-00700 EA-XX-B34-01400 N2T-TR-B32-00160 N2T-TR-B32-00300 N2T-TR-B34-00110 N2T-TR-B34-00220	125	0.25	0.13	0.33	0.18
	250	6.4	3.3	8.4	4.6
	100	<b>B Pattern</b> resistors are bifilar adjustable types. The practical range of adjustment is from $R_{\text{MAX}}$ to $0.15 R_{\text{MAX}}$ , where $R_{\text{MAX}}$ is nominal resistance prior to adjustment (see Resistor Adjustment Instructions).  Recommended Uses: <ul style="list-style-type: none"> <li>span set (EA, N2A)</li> <li>span-shift-versus-temperature compensation (N2T)</li> </ul>			
	200				
	70				
	140				
	16				
	30				
	11				
	22				

**Note 1:** All products shown are RoHS compliant.

Bondable Resistors for Transducers – Selection Chart

GAGE PATTERN AND DESIGNATION Actual size shown on right Insert Desired S-T-C No. in Spaces Marked XX. See Note 1	RESISTANCE IN OHMS		DIMENSIONS			
			PATTERN		MATRIX	
			Length	Width	Length	Width
  <p>N2B-TR-C11-00050 N2B-TR-C12-00100 N2B-TR-C12-00200 N2B-TR-C13-00400 N2B-TR-C13-00800</p>	<b>Before Cut</b>  5 10 20 40 80	<b>After Cut</b>  12 24 48 96 192	0.30	0.20	0.34	0.23
			7.6	5.1	8.6	5.9
			<b>C Pattern</b> grid and adjustable ladder resistors are available in various nominal resistances adjustable to 240% of the initial value. Nominal cutting steps: 4 at 20%; 4 at 10%; and 20 at 1% (see Resistor Adjustment Instructions). Recommended Uses: <ul style="list-style-type: none"> <li>span-shift-versus-temperature compensation</li> </ul>			
  <p>N2F-TR-D01-00005 N2B-TR-D01-00060 N2A-XX-D01-00180 EA-XX-D01-00360 N2K-XX-D01-00500/DP N2K-XX-D01-00750/DP</p>	0.5 6 18 36 50 75		0.35	0.14	0.41	0.20
			8.9	3.6	10.4	5.1
			<b>D Pattern</b> adjustable ladder resistor is a small, single-network pattern available in various alloys and resistances (see Resistor Adjustment Instructions). Resistances listed are nominal fully cut values. Recommended Uses: <ul style="list-style-type: none"> <li>zero-shift compensation (N2F)</li> <li>span-shift-versus-temperature compensation (N2B)</li> <li>span set (EA, N2A, and N2K)</li> </ul>			
  <p>N2F-TR-E01-00005 N2A-XX-E01-00060 N2A-XX-E01-00180 EA-XX-E01-00360 N2K-XX-E01-00500/DP N2K-XX-E01-00750/DP</p>	0.5 6 18 36 50 75		0.35	0.30	0.41	0.36
			8.9	7.6	10.4	9.1
			<b>E Pattern</b> adjustable ladder resistors are similar to the D Pattern but incorporate two adjustable networks on one matrix to provide the differential adjustment capability often required in bridge balance and zero-shift compensation (see Resistor Adjustment Instructions). Resistances listed are nominal fully cut values per network. Recommended Uses: <ul style="list-style-type: none"> <li>zero-shift compensation (N2F)</li> <li>bridge balance (EA, N2A, and N2K)</li> </ul>			
  <p>N2A-XX-H21-00025 N2A-XX-H21-00060  N2B-TR-H22-00010</p>	2.5 6.0  1.0		0.15	0.29	0.21	3.5
			3.8	7.4	5.3	8.9
			<b>H Pattern</b> resistors are adjusted upward in resistance value by rubbing the foil loops with a hand-held or electric pencil eraser. The H21 patterns, produced in constantan alloy, are used for bridge-balance adjustment. (2.5-ohm resistors are typically employed in 350-ohm bridges, and 6.0 ohm in 1000-ohm bridges.) The H22, produced in Balco alloy, is used for bridge zero-versus-temperature adjustment (see Resistor Adjustment Instructions). Resistance values are nominal. Recommended Uses: <ul style="list-style-type: none"> <li>bridge balance (H21)</li> <li>bridge zero-shift compensation (H22)</li> </ul>			

**RESISTANCE WIRE**

While wire does not track the temperature of the strain gages as closely as bondable resistors, there are instances where bondable resistors cannot be used due to limited mounting space. Micro-Measurements stocks two types of resistance wire alloys.

CATALOG NO./ WIRE ALLOY	QTY PER SPOOL	RESISTANCE PER FT (M) NOMINAL	TCR [-10° TO +50°C]	INSULATION	TEMPERATURE RANGE
137-HWN/Manganin	200 ft [61m]	14Ω (46Ω)	± 0.0011%/°F [± 0.002%/°C]	Enamel	+15° to +120°F [-10° to +50°C] (up to +175°F [+80°C] if proper aging is done)
142-JWN/Balco	500 ft [152m]	19Ω (62Ω)	+0.25%/°F [+0.45%/°C]	Enamel	-15° to +300°F [-10° to +150°C]

**NOTE 1:** All products are RoHS compliant.

## Disclaimer

ALL PRODUCTS, PRODUCT SPECIFICATIONS AND DATA ARE SUBJECT TO CHANGE WITHOUT NOTICE.

Vishay Precision Group, Inc., its affiliates, agents, and employees, and all persons acting on its or their behalf (collectively, "Vishay Precision Group"), disclaim any and all liability for any errors, inaccuracies or incompleteness contained herein or in any other disclosure relating to any product.

The product specifications do not expand or otherwise modify Vishay Precision Group's terms and conditions of purchase, including but not limited to, the warranty expressed therein.

Vishay Precision Group makes no warranty, representation or guarantee other than as set forth in the terms and conditions of purchase. **To the maximum extent permitted by applicable law, Vishay Precision Group disclaims (i) any and all liability arising out of the application or use of any product, (ii) any and all liability, including without limitation special, consequential or incidental damages, and (iii) any and all implied warranties, including warranties of fitness for particular purpose, non-infringement and merchantability.**

Information provided in datasheets and/or specifications may vary from actual results in different applications and performance may vary over time. Statements regarding the suitability of products for certain types of applications are based on Vishay Precision Group's knowledge of typical requirements that are often placed on Vishay Precision Group products. It is the customer's responsibility to validate that a particular product with the properties described in the product specification is suitable for use in a particular application.

No license, express, implied, or otherwise, to any intellectual property rights is granted by this document, or by any conduct of Vishay Precision Group.

The products shown herein are not designed for use in life-saving or life-sustaining applications unless otherwise expressly indicated. Customers using or selling Vishay Precision Group products not expressly indicated for use in such applications do so entirely at their own risk and agree to fully indemnify Vishay Precision Group for any damages arising or resulting from such use or sale. Please contact authorized Vishay Precision Group personnel to obtain written terms and conditions regarding products designed for such applications.

Product names and markings noted herein may be trademarks of their respective owners.